



**18. Test and adjustments****WSAH8060 / WMAH100 / K8060 / VM100**

- Use a 2 x 25 to 30Vac / 100 - 120VA transformer.
- Connect the transformer to the AC power connections of the PCB.
- The Velleman transformer colour scheme is specified on the pcb.

⚠ **Careful : Other brands may feature a different scheme !**

Y: yellow, R: red, B: blue, G: grey.



### Transformer supplied by ESR Electronic Components Ltd

ESR Order Code: **325-030**

Model: **VTX-146-120-230**

Cross reference chart for transformer wiring

P8060-2 Board Ref	Velleman Colour	ESR Colour	Output Voltage
<b>Y</b> AC	Yellow	Yellow	30Vac #1
<b>R</b> AC-0	Red	Orange	0Vac #1
<b>B</b> AC	Blue	Red	30Vac #2
<b>G</b> AC-0	Grey	Black	0Vac #2